

## A1D - Update guide


v.0.0.1

This document is a guide for updating PJ-series and the MB-series with the DVTLight A1D, from the website hosted by the DVTLight A1D.

### DISCLAIMER

*If you only see Bootloader and no version in the startup, then contact DVTLight.*

This Guide can **only** be used with Lamps that have bootloader v.0.2.0 and up to v.0.3.3. **It can not** update a Lamp with just the Bootloader present at startup .



**NOT OK**



**OK**



**OK**

---

## UPDATE PJMB FROM WEBSITE PROCESS

1. Connect A1D via USB-C to a Windows PC
2. Open preferred browser (Chrome,Firefox, Edge etc)
3. Go to **2.2.2.2**
4. Navigate to **Device Firmware**
5. In the dropdown choose **PJMB v.0.1.46**
6. Press **Start Upload**

### 1. Connect A1D via USB-C to a Windows PC

Connect the DVTLight A1D to a Windows PC, via a USB-C. The connect the DMX to the DVTLight A1D




### 2. Open a preferred browser(Chrome, Firefox, Edge, etc.)

Now open a preferred browserwindow, the DVTLight A1D works with Chrome, Firefox, Edge etc.


### 3. Go to 2.2.2.2

Navigate to the URL-bar and write **2.2.2.2** and press **ENTER**. You will be presented with something similar to this:




## 4. Navigate to Device Firmware

Now press the **Device Firmware** tab, like shown below:




In the dropdown, it is possible to choose the desired firmware version. It is set to default to **PJMB v.0.1.46**. Be aware that the Delete button is not pressed, if pressed the firmware will be deleted from the DVTlight A1D.



## 5. Start Upload

After choosing the desired Firmware from the dropdown press **Start Upload**. This will take some time, make sure to not press the **Start Upload** button multiple times. Put wait till the progress bar and the lamp has reset.



## Update Process with a lamp with Bootloader v.0.2.0

Info DMX RDM Device Firmware A1D Firmware

Device Firmware

Update Firmware

Browse... No file selected.


PJMB v0.1.43

Connected

Build: Jan 23 2024 09:13:01  
Software Version: A1D-v0.0.1

WiFi

P



## Update Process with a lamp with Bootloader v.0.3.3

Info DMX RDM Device Firmware A1D Firmware

Device Firmware

Update Firmware

Browse... No file selected.

PJMB v0.1.43

Connected

Build: Jan 23 2024 09:13:01  
Software Version: A1D-v0.0.1

WiFi

P

