

# StorEdge<sup>®</sup> Three Phase Inverter

SE5K-RWS / SE7K-RWS / SE8K-RWS / SE10K-RWS



STOREDGE<sup>®</sup>

## Ideal solution for three phase installations with battery storage

- Simple installation with single inverter for managing both PV production and battery storage
- More energy using DC-coupled solution architecture that stores PV power directly to the battery without AC conversion losses
- Quick and easy inverter commissioning directly from a smartphone using the SolarEdge SetApp
- Designed to eliminate high voltage during installation, maintenance, or firefighting for enhanced safety
- Built-in module-level monitoring and full visibility of battery status, PV production, and self-consumption data
- Allows connection of low voltage 48V batteries from multiple battery vendors to provide greater flexibility

# / StorEdge® Three Phase Inverter

SE5K-RWS / SE7K-RWS / SE8K-RWS / SE10K-RWS

Applicable for inverters with part number	SEXK-XXS48XXXX				
	SE5K-RWS	SE7K-RWS	SE8K-RWS	SE10K-RWS	
<b>OUTPUT</b>					
Rated AC Power Output	5000	7000	8000	10000	VA
Maximum AC Power Output	5000	7000	8000	10000	VA
AC Output Voltage — Line to Line / Line to Neutral (Nominal)	380/220 ; 400/230				Vac
AC Output Voltage — Line to Neutral Range	184 - 264.5				Vac
AC Frequency	50/60 ± 5				Hz
Maximum Continuous Output Current (per Phase)	8	11.5	13	16	A
Residual Current Detector / Residual Current Step Detector	300 / 30				mA
Grids Supported — Three Phase	3 / N / PE (WYE with Neutral)				
Utility Monitoring, Islanding Protection, Configurable Power Factor, Country Configurable Thresholds	Yes				
<b>INPUT PV</b>					
Maximum DC Power (Module STC)	6750	9450	10800	13500	W
Transformer-less, Ungrounded	Yes				
Maximum Input Voltage	900				Vdc
Nominal DC Input Voltage	750				Vdc
Maximum Input Current	8.5	12	13.5	16.5	Adc
Reverse-Polarity Protection	Yes				
Ground-Fault Isolation Detection	700kΩ Sensitivity				
Maximum Inverter Efficiency	98				%
European Weighted Efficiency	97.3	97.4	97.6		%
<b>INPUT BATTERY</b>					
Supported Battery Types <sup>(1)</sup>	SolarEdge Home Battery – Low Voltage BAT-05K48M0B-01 LG Chem RESU3.3, RESU6.5, RESU10, RESU12, RESU13 <sup>(2)</sup> , BYD Battery-Box LV 3.5, 7.0, 10.5, 14.0 BYD Battery-Box Premium LVS 4.0, 8.0, 12.0, 16.0, 20.0, 24.0				
Number of Batteries per Inverter	1				
Maximum DC Power	5000				W
Input Voltage Range	40-62				Vdc
Maximum Continuous Input Current	130				Adc
Peak Battery to Grid discharge Efficiency	96.1				%
Battery Communication	CAN				
<b>ADDITIONAL FEATURES</b>					
Supported Communication Interfaces	2 x RS485, Ethernet, ZigBee communications for Smart Energy <sup>(3)</sup> , Wi-Fi <sup>(4)</sup> , Built-in cellular (optional)				
<b>STANDARD COMPLIANCE</b>					
Safety	IEC-62109				
Grid Connection Standards <sup>(4)</sup>	VDE 0126-1-1, VDE-AR-N-4105, G98 / G99				
Emissions	IEC61000-6-2, IEC61000-6-3, IEC61000-3-11, IEC61000-3-12				
RoHS	Yes				
<b>INSTALLATION SPECIFICATIONS</b>					
AC Output – Cable Gland Diameter	15 - 21				mm
Battery DC – Cable Gland Diameter	2 x 8-11				mm
PV DC Input	2 x MC4 pair				
Dimensions (H x W x D)	853 x 316 x 193				mm
Weight	37				kg
Operating Temperature Range	-40 to +60				°C
Cooling	Internal and external fans				
Noise	< 50				dBA
Protection Rating	IP65 — outdoor and indoor				
Mounting	Brackets provided				

(1) For supported battery models refer to <https://www.solaredge.com/sites/default/files/se-storedge-3ph-inverter-supported-system-configurations-app-note.pdf>.

(2) When connecting two batteries together with RESU Plus box, any combination of LG RESU 3.3, 6.5, 10 and 12 is supported. RESU 13 can only be connected to another RESU 13.

(3) For more information refer to: <https://www.solaredge.com/sites/default/files/se-zigbee-plug-in-wireless-communication-for-setapp-datasheet.pdf>.

(4) Wi-Fi connectivity requires an external antenna. For more information refer to: <https://www.solaredge.com/sites/default/files/se-wifi-zigbee-antenna-datasheet.pdf>.

For all standards, see the Certifications category in the Downloads page: <http://www.solaredge.com/groups/support/downloads>.