

LF power amplification

Socket type: Noval

Cathode type: oxide, indirect heating

Envelope: glass, miniature

Mass: 20 g

Filament voltage: 6,3 V

Filament current: 0,45 - 0,53 A

Anode voltage: 250 V

Anode current: 33 - 55 mA

Anode power: 12 W

Grid1 voltage: -12,5 V

Grid2 voltage: 250 V

Steepness: 3,8 - 6 mA/V

Reverse grid current: 0,5 μ A

Microphonic noise: 200 mV

