



raditeq

Data Sheet

RadiPower® 3000 series

RF Power Meter

Fast

Accurate

Easy to use



raditeq.com

Publish date: 19/10/2020



RadiPower[®] 3000 Series

Fast Synchronous Power Measurements · Flexible

Fast

Accurate

Easy to use

Raditeq offers the RadiPower model RPR3006W to comply with the measurement requirements of the ETSI 300 328 and 301 893 standards for wideband data transmission systems, like IEEE 802.11TM, Bluetooth and ZigbeeTM including the new WI-FI 6E (6 GHz). The RPR3006W now covers a measurements range from 10 MHz to 6 (8) GHz.

Extremely Fast

In order to achieve this measurement requirements of the ETSI standards the sampling speed of the RadiPower power sensor has been increased to maximum 5 MS/s. The RPR3006W is also equipped with a hardware trigger input/output that allows synchronous power measurements of wideband data transmission devices with multiple inputs/outputs (MIMO).

Accurate

Next to speed, accuracy is another main requirement when performing RF power measurements of wireless devices. The RPR3006W allows high precision RF power measurements with a high dynamic range of 60 dB. The power meter provides a accuracy of $\pm 0,2$ dB and is well within the requirements for measurements in accordance to ETSI standards.

Easy to use

The RadiPower Wireless is equipped with an USB interface which enables direct connection of the Power sensors to a PC USB port. Together with the RadiPower USB power sensor a RadiMation FREE freeware package is delivered to enable direct control of the power meter settings and display the measurement results on the PC screen. The RadiMation Freeware also enables synchronous triggering of multiple RadiPower Wireless power sensors.

'Burst' mode

The RadiMation Freeware includes a 'Burst' mode with user selectable measurement speed/time to capture the wideband Burst/Pulse signals and calculate the measurement parameters, maximum RMS power, duty cycle, medium utilization and maximum sequence time. This mode is fully compliant with the measurement methods as defined in the ETSI standards for wideband data transmission systems EN 300 328 (2,4 GHz) and EN 301 893 (5 GHz). In burst mode, the RadiPower can store the information of 100.000 bursts and observation time up to 60 seconds. For each burst the average power and timing data is stored in the buffer. The RadiPower uses a sample speed of 1 or 5 MSps in combination with a RMS detector to ensure correct measurements on wideband modulating transceivers.

Synchronized measurements

For MIMO devices with for example six antenna ports, an equal amount of RPR3006W power heads can be daisy-chained using the MMCX connectors enabling synchronised triggering of all six RadiPower meters. RadiMation Freeware captures the samples of each power meter simultaneously and calculates the total combined power according to the ETSI 300 328 standard.

Software support

The standard delivered RadiMation Freeware supports all RadiPower measurement modes. Using the instrument command codes the RadiPower Wireless can be used with any other software control package.

RadiCentre® Technical Specifications

Model	RPR3006W
Measuring function	RMS power, peak max hold and Burst mode
Measurement speed	10, 50, 100 kS/s, 1, 5, 10, 20, 33 MS/s ⁽¹⁾
Storage capacity	100.000 samples 100.000 bursts
Resolution	0,01 dB
Measuring units	dBm or Watt
Zero adjustment	Not required
Input damage level	> +20 dBm
Measurement range & accuracy	
Frequency range	10 MHz tot 6 GHz
Power measuring range	-50 dBm to +10 dBm @ 10 MHz to 6 GHz
Frequency response accuracy (at 23° C ± 2° C)	+/- 0,2 dB
Linearity error	0,05 dB + 0,005 dB/dB
Temperature effect	0,15 dB max over full temperature range
Deviation from CW for signals with high Crest factor	< 0,2 dB
VSWR	
Max SWR: < 100 MHz	1,10
100 MHz to 1 GHz	1,10
1 GHz to 6 GHz	1,15 typical (max 1,18)
Connections & Dimensions	
Dimensions of measuring device	124 * 32 * 32 mm
RF input connector	N type precision
Data connector (power head side)	USB mini type B
Power Consumption	
Supply voltage	+5Vdc from USB port (4,75 V to 5,25 V)
Current consumption (USB)	Max. 250 mA
Environmental conditions	
Temperature range (operating)	0° to 40° Celsius
Temperature range (storage)	-20 to 85° C
Relative humidity	10 - 90% (non-condensing)
Compliance	
EMC	EN 61326
Low Voltage	N/A
Warranty	3 year (misuse excluded)*

- In burst mode only 1 and 5 MS/s can be set and used.
 - All specifications are measured after 10 minutes warm-up time and 0dBm unless specified otherwise.
 - Typical specifications indicate that the measured values are met on at least 80% of the points.
 - Three years warranty will be granted only after you register the product at www.raditeq.com. Without registration, a 1 year warranty period applies.

For more information about the current and new Raditeq products at:

T: +31 348 200 100 M: Sales@raditeq.com

W: www.raditeq.com



raditeq

Raditeq B.V. | Vijzelmolenlaan 3 | 3447GX Woerden | The Netherlands

www.raditeq.com | T: +31 348 200 100