

IP67 - Waterproof

iriBelt II is IP67 waterproof when the headset connector is mated. It is NOT waterproof unmated and with the rubber protection cap only.

Video Instructions

At <https://www.youtube.com/watch?v=Yfdlv9tSLU8> a video manual is available.

Cleaning / maintenance

Do not use chemicals or solvents to clean your iriBelt II. Use only a damp cloth, and lukewarm freshwater and wipe/rinse carefully the visible surfaces on your iriBelt II

Saltwater may be removed with lukewarm freshwater. Rinse carefully over the unit to remove any salt in and around the connector and the swivel belt clip.

Do not allow any water to enter the connector when unmated.

Pressure, friction, sharp objects, etc. can damage the product and the warranty may be void.

If your iriBelt II is not in use for a longer period, remember to charge the battery every 2 weeks, to extend battery life.

Warranty

IriBelt II is covered by a limited one (1) year warranty against manufacturing defects, excluding battery.

Declaration of Conformity

Refer to www.iridiumcomms.dk/downloads/Declaration_of_Conformity_iriBelt2_0.pdf

Disposal

iriBelt II contain a Li-Ion battery and a PCB, and must be disposed of according to local laws.

Height wo/w antenna	127/207 mm	Waterproof	IPX7 (Headset Mated)	
Width	80 mm	Battery	800 mAh Li-Ion	
Depth wo/w belt clip	28/41 mm	Temp. range	-15 to + 55 degree Celsius	
Weight	210 g	Range	High Sound Quality	Up to 50 meters
			Standard Sound Quality	Up to 250 meters

QUICK START USER GUIDE



Congratulations on your new IriBelt II

Congratulation on your new IWCS Product. We hope you will enjoy the benefits of trouble free High Quality Intercom. Please read these instructions carefully before first use.

iriBelt II

In the box

- iriBelt II
- Charging Pad
- USB cable for charging pad
- Quick Start Guide

Please contact your local dealer immediately if something is missing.

Before first use

Charge the battery to full before first use.

Front side view

Headset Connector

Align RED dots with your headset connector
or
Push/Pull connector. Do not twist or bend

Antenna

FRAGILE - Do not try to bend or twist the antenna

PTT 1

PTT 2

Volume Down

In Master Reset Mode, this button reduces the sound quality and enhances the range. When selected, press MODE button to save.

Volume Up

In Master Reset Mode, this button sets the sound quality high and the range to standard. When selected, press MODE button to save.

MODE button

From OFF Position:

Press & hold for 2 sec	ON
Press & hold for 5 sec	Pairing Mode 1 Mobile Phone
Press & hold for 10 sec	Pairing Mode 2 Intercom
Press & hold for 15 sec	Pairing Mode 3 Peer-To-Peer*
Press & hold for 25 sec	Master Reset / Range setting
Press & Hold for >30 sec	Automatic OFF

Indicator LED

GREEN	Flash	ON
BLUE	Fast Flash	Pairing mode
BLUE	Slow Flash	Paired / Active
RED	Flash / 5 sec	Low Battery
RED	Flash	Charging
When fully charged light turns OFF		

From ON Position:

Press & Hold for 2 sec	OFF
------------------------	-----

* When pairing Peer-To-Peer, one unit must be in Pairing Mode 2 and the other in Pairing Mode 3


iriBelt II

Rear side view

Swivel Belt Clip

Serial Number

Inductive Charging Area



Charging

iriBelt II has an advanced inductive battery charge circuit. The 800 mAh Li-Ion battery provides long life and long operational time - up to 24 hours.

When iriBelt II is turned ON, a Voice Prompt will inform of the present battery status with a "Battery High" (80-100%), "Battery Medium" (20-80%) or "Battery Low" (10-20%). At the 10% battery level there is an automatic Cut Off, which will turn off iriBelt II.

When the Low Battery level is reached, the Status LED on the front, will flash RED every 5 seconds.

To charge iriBelt II place the unit on top of the Qi wireless charging pad. The Status LED will flash RED every 2 seconds, as long as the battery is being charged. When the battery is fully charged the Status LED will stop flashing and turns off.

It doesn't matter if iriBelt II is ON or OFF during charging.

