


B² andio




MODEL: ES 6.1 Product id: ES61CF12









Α	ø 165
В	ø 142
С	ø 154

G	ø 47
Н	28

1	ø 55	
J	24	

D	ø 104
Ε	66
F	5

Power handling*:

Sensitivity:

Nominal impedance:

Frequency response:

DC Resistance (Re): Magnet weigth (Oz): 100 Watts

90.2 dB

4Ω

45 ~ 20.000 Hz

3.3Ω 20 Oz

 B^2 and io


www.b2audio.com www.facebook.com/sweetlikedanish www.instagram.com/b2_audio www.youtube.com/b2audio www.twitter.com/b2_audio

^{*}It is essential that our speakers are given time to allow the suspension to soften up. Depending on usage, this may take several weeks. While this process is undergoing, it is not recommended to apply full amplification power according to the speakers specs. Once the moving parts have been broken in, the performance of your subwoofer will increase.

B² andio



MODEL: EL12K Product id: EL12KD214



ENCLOSURE SUGGESTIONS

SEALED: 40 L / 1.413 cu.ft (net), Qtc 0.773

PORTED: 50 L / 1.766 cu.ft (net), 2 x 3" ports, length 8,24"

FB 42 Hz / F-3 dB 37.2 Hz

Power handling*: 350 W Sensitivity (2.83 V/1 m): 90.5 dB Dual 2Ω Nominal impedance: X-Max: 12 mm Equivalent Compliance (Vas): 70.1 L Free Air Resonance (Fs): 33.6 Hz Electrical "Q" (Qes):
Mechanical "Q" (Qms):
Total Speaker "Q" (Qts): 0.76 5.48 0.67 DC Resistance (Re): 2.1Ω 50 Oz Magnet weigth (Oz):



www.b2audio.com

www.facebook.com/sweetlikedanish

www.instagram.com/b2_audio

www.youtube.com/b2audio www.twitter.com/b2 audio


*It's essential that our speakers are given time to allow the suspension to soften up. Depending on use, this may take several weeks. While this process is undergoing, it is not recommended to apply full amplification power according to the speakers specs. Once the moving parts have been broken in, the performance of your speaker will increase. Abuse of the unit is **not** covered by warranty. The warranty does not cover (1) Speakers that have been used for spl purpose in competitions, (2) Damage caused by amplifier clipping or distortion, (3) Exposure to water, oil, solvent & excessive temperatures +/- (4) Transportation damages.





MODEL: IS10 MODEL: IS12

PRODUCT ID: IS10D215 PRODUCT ID: IS12D215



ENCLOSURE SUGGESTIONS						
	SEALED	PORTED COMPACT	PORTED	BP 4 TH		
IS10	17,42 L / 0.615 CU.FT QTC 0.429	21.65 L / 0.765 CU.FT P: 3" L: 11.68" FB: 42 HZ	35 L / 1.236 CU.FT P: 4" L: 13.32" FB 40 HZ	S: 22 L / 0.776 CU.FT P: 44 L / 1.552 CU.FT P. AREA: 16 SQ.IN L: 10"		
IS12	25 L / 0.882 CU.FT QTC 0.451	35 L / 1.236 CU.FT P: 4" L: 11.71" FB: 40 HZ	55 L / 1.942 CU.FT P: 4" L: 9.18" FB 37 HZ	S: 22 L / 0.776 CU.FT P: 55 L / 1.942 CU.FT P. AREA: 16 SQ.IN L: 10"		

	IS10	IS12
Power handling*:	600 W	600 W
Sensitivity (2.83 v/1m):	89.8 dB	92.03 dB
Nominal impedance:	Dual 2Ω	Dual 2Ω
X-Max:	18 mm	18 mm
Equivalent Compliance (Va	s): 20 L	46.7 L
Free Air Resonance (Fs):	37.9 Hz	34.5 Hz
Electrical "Q" (Qes):	0.36	0.38
Mechanical "Q" (Qms):	4.98	5.36
Total Speaker "Q" (Qts):	0.34	0.36
DC Resistance (Re):	2.1 Ω	$2.1~\Omega$
Magnet weigth (Oz):	2 x 58 Oz	2 x 58 Oz
Dimensions (mm): IS10	A: 264 B: 245 C: 234 D: 168 E: 62 F:16 G: 129	

A: 318 B: 297 C: 282 D: 168 E: 62 F:16 G: 142




Dimensions (mm): IS12

www.b2audio.com www.facebook.com/sweetlikedanish www.instagram.com/b2_audio www.youtube.com/b2audio www.twitter.com/b2_audio





MODEL: IS15 Product id: IS15D213



ENCLOSURE SUGGESTIONS

SEALED: 40 L / 1.412 cu.ft (net), Qtc 0.615

PORTED COMPACT: 55 L / 1.942 cu.ft (net), 2 x 3" ports, length 8"

FB 42 Hz / F-3 dB 43 Hz

PORTED: 120 L / 4.237 cu.ft (net), 2 x 4" ports, length 8,46"

FB 35 Hz / F-3 dB 33 Hz

BANDPASS 4. ORDER: S. 60 L / 2.118 cu.ft - P. 120 L / 4.237 cu.ft,

2 x 6" ports, length 4,55"

Power handling*: 600 W Sensitivity: 91.2 dB Nominal impedance: Dual 2Ω X-Max: 18 mm Equivalent Compliance (Vas): 167.88 L Free Air Resonance (Fs): 27.56 Hz Electrical "Q" (Qes): Mechanical "Q" (Qms): Total Speaker "Q" (Qts): 0.407 3.838 0.367 DC Resistance (Re): 2.2Ω 2 x 58 Oz Magnet weigth (Oz):



www.b2audio.com www.facebook.com/sweetlikedanish www.instagram.com/b2_audio www.youtube.com/b2audio www.twitter.com/b2_audio

*It's essential that our speakers are given time to allow the suspension to soften up. Depending on use, this may take several weeks. While this process is undergoing, it is not recommended to apply full amplification power according to the speakers specs. Once the moving parts have been broken in, the performance of your speaker will increase. Abuse of the unit is **not** covered by warranty. The warranty does not cover (1) Speakers that have been used for spl purpose in competitions, (2) Damage caused by amplifier clipping or distortion, (3) Exposure to water, oil, solvent & excessive temperatures +/-.